

Part Number Explanation

DIAMETER	
Code	Description
1	5 / 16"
2	3 / 8"
3	9 / 16"
4	3 / 4"
5	13 / 16"
6	7 / 8"
7	15 / 16"
8	1 - 1 / 16"
9	1 - 3 / 8"

DC WORKING VOLTAGE	
Code	Description
A	1 KV
B	2 KV
C	3 KV
D	4 KV
E	5 KV
F	6 KV
G	7 KV
H	8 KV
I	9 KV
J	10 KV
K	12 KV
L	15 KV
M	18 KV
N	20 KV
O	25 KV
P	30 KV

CAPACITANCE PF.	
Description	
First two digits are significant figures. The last digit is a multiplier	

CAPACITANCE TOLERANCE	
Code	Description
J	±5%
K	±10%
M	±20%
Z	+80 / -20%

LEAD SPACING	
Code	Description
A	1 / 4"
B	3 / 8"
C	1 / 2"

4 - J - 102 - M - C

Code No. Example:

Capacitor Specs: 1000 PF, ±20%, 10 KVDC